



Электродвигатели с электромагнитным тормозом



тип двигателя	Мощность		Обороты [min ⁻¹]	Тип Тормоза											
	[kW]	[KM]		HZg	HPS	H2SP	2HPS	H	HS	H2S	HPSX	2HZg	HSX	NEX	NE
2p=2 ns=3000 об/мин															
Sg 56-2A	0,09	0,12	2800		HPS06		2HPS06				HPSX06				
Sg 56-2B	0,12	0,17	2800		HPS06		2HPS06				HPSX06				
Sg 63-2A	0,18	0,25	2760		HPS06	H2SP63	2HPS06	H63			HPSX06				
Sg 63-2B	0,25	0,33	2760		HPS06	H2SP63	2HPS06	H63			HPSX06				
Sh 71-2A	0,37	0,50	2800		HPS08	H2SP71	2HPS08	H71		H2S71	HPSX08				
Sh 71-2B	0,55	0,75	2790		HPS08	H2SP71	2HPS08	H71		H2S71	HPSX08				
Sh 80-2A	0,75	1,0	2800		HPS10	H2SP80	2HPS10	H80		H2S80	HPSX10				
Sh 80-2B	1,1	1,5	2780		HPS10	H2SP80	2HPS10	H80		H2S80	HPSX10				
Sh 90S-2	1,5	2,0	2835	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90			
Sh 90L-2	2,2	3,0	2855	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90			
Sg 100L-2	3,0	4,0	2905	HZg100	HPS12	H2SP100	2HPS12	H100		H2S100	HPSX12	2HZg100			
Sg 112M-2	4,0	5,5	2865	HZg112	HPS14	H2SP112	2HPS14	H112		H2S112	HPSX14	2HZg112		NEX05	NE05
Sg 132S-2A	5,5	7,5	2910	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10
Sg 132S-2B	7,5	10,0	2920	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10
Sg 160M-2A	11,0	15,0	2930	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16
Sg 160M-2B	15,0	20,0	2920	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16
Sg 180M-2	22,0	30,0	2920		HPS20	H2SP180	2HPS20				HPSX20			NEX25	NE25
Sg 200L-2A	30,0	40	2960		HPS25	H2SP200	2HPS25				HPSX25			NEX30	NE30
Sg 200L-2B	37,0	50	2960		HPS25	H2SP200	2HPS25				HPSX25			NEX30	NE30
Sg 225M-2	45,0	60	2968		HPS25	H2SP200	2HPS25				HPSX25			NEX50	NE50
Sg 250M-2	55,0	75	2970		HPS25	H2SP200	2HPS25				HPSX25			NEX50	NE50
Sg 280S-2	75,0	100	2977						HS900		HPSX25		HSX630	NEX70	NE70
Sg 280M-2	90,0	125	2970						HS900		HPSX25		HSX630	NEX100	NE100
Sg 315S-2	110	150	2975						HS900				HSX1000	NEX100	NE100
Sg 315M-2A	132	180	2975						HS900				HSX1000	NEX160	NE160
Sg 315M-2B	160	217	2975						HS900				HSX1000	NEX160	NE160
2p=4 ns=1500 об/мин															
Sg 56-4A	0,06	0,08	1400		HPS06		2HPS06				HPSX06				
Sg 56-4B	0,09	0,12	1380		HPS06		2HPS06				HPSX06				
Sg 63-4A	0,12	0,17	1380		HPS06	H2SP63	2HPS06	H63			HPSX06				
Sg 63-4B	0,18	0,25	1380		HPS06	H2SP63	2HPS06	H63			HPSX06				
Sh 71-4A	0,25	0,33	1380		HPS08	H2SP71	2HPS08	H71		H2S71	HPSX08				
Sh 71-4B	0,37	0,50	1360		HPS08	H2SP71	2HPS08	H71		H2S71	HPSX08				
Sh 80-4A	0,55	0,75	1400		HPS10	H2SP80	2HPS10	H80		H2S80	HPSX10				
Sh 80-4B	0,75	1,0	1390		HPS10	H2SP80	2HPS10	H80		H2S80	HPSX10				
Sh 90S-4	1,1	1,5	1405	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90			
Sh 90L-4	1,5	2,0	1410	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90			
Sg 100L-4A	2,2	3,0	1425	HZg100	HPS12	H2SP100	2HPS12	H100		H2S100	HPSX12	2HZg100			
Sg 100L-4B	3,0	4,0	1415	HZg100	HPS12	H2SP100	2HPS12	H100		H2S100	HPSX12	2HZg100			
Sg 112M-4	4,0	5,5	1435	HZg112	HPS14	H2SP112	2HPS14	H112		H2S112	HPSX14	2HZg112		NEX05	NE05
Sg 132S-4	5,5	7,5	1450	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10
Sg 132M-4	7,5	10,0	1450	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10
Sg 160M-4	11,0	15,0	1460	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg132		NEX16	NE16
Sg 160L-4	15,0	20,0	1460	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16
Sg 180M-4	18,5	25,0	1470		HPS20	H2SP180	2HPS20				HPSX20			NEX25	NE25
Sg 180L-4	22,0	30,0	1465		HPS20	H2SP180	2HPS20				HPSX20			NEX25	NE25
Sg 200L-4	30,0	40	1472		HPS25	H2SP200	2HPS25				HPSX25			NEX30	NE30
Sg 225S-4	37,0	50	1475		HPS25	H2SP200	2HPS25				HPSX25			NEX30	NE30
Sg 225M-4	45,0	60	1480		HPS25	H2SP200	2HPS25				HPSX25			NEX30	NE30
Sg 250M-4	55,0	75	1483		HPS25	H2SP200	2HPS25				HPSX25			NEX50	NE50
Sg 280S-4	75,0	100	1485						HS900		HPSX25		HSX630	NEX70	NE70
Sg 280M-4	90,0	125	1485						HS900		HPSX25		HSX630	NEX100	NE100
Sg 315S-4	110	150	1480						HS900				HSX1000	NEX100	NE100
Sg 315M-4A	132	180	1487						HS1600				HSX1000	NEX160	NE160
Sg 315M-4B	160	217	1490						HS1600				HSX1000	NEX160	NE160

тип двигателя	Мощность		Обороты [min ⁻¹]	Тип Тормоза												
	[kW]	[KM]		HZg	HPS	H2SP	2HPS	H	HS	H2S	HPSX	2HZg	HSX	NEX	NE	
2p=6 ns=1000 об/мин																
Sg 56-6B	0,06	0,08	900		HPS06		2HPS06						HPSX06			
Sg 63-6A	0,09	0,12	820		HPS06	H2SP63	2HPS06	H63					HPSX06			
Sg 63-6B	0,12	0,17	880		HPS06	H2SP63	2HPS06	H63					HPSX06			
Sh 71-6A	0,18	0,25	890		HPS08	H2SP71	2HPS08	H71		H2S71			HPSX08			
Sh 71-6B	0,25	0,33	860		HPS08	H2SP71	2HPS08	H71		H2S71			HPSX08			
Sh 80-6A	0,37	0,50	910		HPS10	H2SP80	2HPS10	H80		H2S80			HPSX10			
Sh 80-6B	0,55	0,75	900		HPS10	H2SP80	2HPS10	H80		H2S80			HPSX10			
Sh 90S-6	0,75	1,0	915	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90				
Sh 90L-6	1,10	1,5	920	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90				
Sg 100L-6	1,50	2,0	945	HZg100	HPS12	H2SP100	2HPS12	H100		H2S100	HPSX12	2HZg100				
Sg 112M-6	2,20	3,0	960	HZg112	HPS14	H2SP112	2HPS14	H112		H2S112	HPSX14	2HZg112		NEX05	NE05	
Sg 132S-6	3,00	4,0	950	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10	
Sg 132M-6A	4,00	5,5	950	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10	
Sg 132M-6B	5,50	7,5	950	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10	
Sg 160M-6	7,50	10,0	960	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16	
Sg 160L-6	11,0	15,0	960	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16	
Sg 180L-6	15,0	20,0	975		HPS20	H2SP180	2HPS20						HPSX20		NEX25	NE25
Sg 200L-6A	18,5	25,0	980		HPS25	H2SP200	2HPS25						HPSX25		NEX30	NE30
Sg 200L-6B	22,0	30,0	981		HPS25	H2SP200	2HPS25						HPSX25		NEX30	NE30
Sg 225M-6	30,0	40,0	982		HPS25								HPSX25		NEX50	NE50
Sg 250M-6	37,0	50,0	985						HS900				HPSX25	HSX630	NEX50	NE50
Sg 280S-6	45,0	60,0	985						HS900					HSX630	NEX70	NE70
Sg 280M-8	55,0	75,0	985						HS900					HSX630	NEX100	NE100
Sg 315S-6	55,0	75,0	985						HS900					HSX1000	NEX100	NE100
Sg 315M-6A	75,0	100	984						HS1600					HSX1000	NEX160	NE160
Sg 315M-6B	90,0	125	985						HS1600					HSX2500	NEX160	NE160
2p=8 ns=750 об/мин																
Sg 63-8A	0,04	0,06	670		HPS06	H2SP63	2HPS06	H63					HPSX06			
Sg 63-8B	0,06	0,08	670		HPS06	H2SP63	2HPS06	H63					HPSX06			
Sh 71-8A	0,09	0,12	680		HPS08	H2SP71	2HPS08	H71		H2S71			HPSX08			
Sh 71-8B	0,12	0,17	670		HPS08	H2SP71	2HPS08	H71		H2S71			HPSX08			
Sh 80-8A	0,18	0,25	680		HPS10	H2SP80	2HPS10	H80		H2S71			HPSX10			
Sh 80-8B	0,25	0,33	680		HPS10	H2SP80	2HPS10	H80		H2S80			HPSX10			
Sh 90S-8	0,37	0,50	695	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90				
Sh 90L-8	0,55	0,75	675	HZg90	HPS10	H2SP90	2HPS10	H90		H2S90	HPSX10	2HZg90				
Sg 100L-8A	0,75	1,00	710	HZg100	HPS12	H2SP100	2HPS12	H100		H2S100	HPSX12	2HZg100				
Sg 100L-8B	1,10	1,50	705	HZg100	HPS12	H2SP100	2HPS12	H100		H2S100	HPSX12	2HZg100				
Sg 112M-8	1,50	2,00	720	HZg112	HPS14	H2SP112	2HPS14	H112		H2S112	HPSX14	2HZg112		NEX05	NE05	
Sg 132S-8	2,20	3,00	710	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10	
Sg 132M-8	3,00	4,00	710	HZg132	HPS16	H2SP132	2HPS16	H132		H2S132	HPSX16	2HZg132		NEX10	NE10	
Sg 160M-8A	4,00	5,50	705	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16	
Sg 160M-8B	5,50	7,50	710	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16	
Sg 160L-8	7,50	10,0	705	HZg160	HPS18	H2SP160	2HPS18	H160		H2S160	HPSX18	2HZg160		NEX16	NE16	
Sg 180L-8	11,0	15,0	730		HPS20	H2SP180	2HPS20						HPSX20		NEX25	NE25
Sg 200L-8	15,0	20,0	733		HPS25	H2SP200	2HPS25						HPSX25		NEX30	NE30
Sg 225S-8	18,5	25,0	735		HPS25	H2SP200	2HPS25						HPSX25		NEX50	NE50
Sg 225M-8	22,0	30,0	735		HPS25	H2SP200	2HPS25						HPSX25		NEX50	NE50
Sg 250M-8	30,0	40,0	738		HPS25	H2SP200	2HPS25						HPSX25		NEX50	NE50
Sg 280S-8	37,0	50,0	737										HPSX25	HSX630	NEX70	NE70
Sg 280M-8	45,0	60,0	737						HS900				HPSX25	HSX630	NEX100	NE100
Sg 315S-8	55,0	75,0	735						HS900					HSX1000	NEX100	NE100
Sg 315M-8A	75,0	100	737						HS1600					HSX1000	NEX160	NE160
Sg 315M-8B	90,0	125	737						HS1600					HSX2500	NEX160	NE160

